INPUT Frequency 10 MHz, ±2 x 10⁻⁶ Level +7 dBm ±5 dB into 50 ohms OUTPUT Frequency 100 MHz Level +13 dBm ±2 dB into 50 ohms STABILITY Output Phase Noise L(f) (Free-Running) -128 dBc/Hz 100 Hz 1 kHz -155 dBc/Hz 10 kHz -170 dBc/Hz 100 kHz -171 dBc/Hz Aging $\pm 1 \times 10^{-6}$ per year after 30 days operating, typical **Temperature Stability** $\pm 5 \times 10^{-7}$ free-running from 0 to $\pm 50^{\circ}$ C, (Ref. +25°C) Phase Lock Alarm TTL Locked: +3.5 VDC to +5.2 VDC (Hi) Out-of-Lock: +0.8 VDC max (Lo) Phase Lock Voltage Monitor Voltage monitor pin supplied SPECTRAL PURITY Harmonics ≤-30 dBc Sub-Harmonics ≤-50 dBc PLL Divider Products ≤-60 dBc Spurious ≤-70 dBc MECHANICAL Dimensions 2.5 x 3.5 x 0.8" Connectors SMA's and solder pins on side Feed-thru terminals for lock alarm, supply and phase lock voltage monitor

Packaging

Mounting

Loop BW

CRYSTAL

SC-cut

REVISION RECORD REV DATE DWN AUTH 10-11-11 Initial Release PAC -Nickel-plate machined aluminum housing Tapped holes on sides, 16 places Through holes, 4 places Threaded inserts on base, 4 places POWER REQUIREMENTS 16 X .060-80 Supply Voltage Ø0.0930 Dia. Threaded Inserts Mounting Holes 2.500 +15 VDC ±5% 1.750 ~ 1.665 Warm-Up Power - 1.490 ≤8 Watts at start-up for 5 minutes - 1 250 Φ - 1.200 at +25° C - 1.010 **Total Power** ≤5 Watts at steady state +25°C ADJUSTMENT 3.50 - 0.000 - 0.000 Target Bandwidth: < 5 Hz Type 2 Loop - 1.010 -0 - 1.200 - 1.250 - 1.490 _- 1.665 1.750 _____ 4 X 2-56 hreaded Inserts - 0.240 0.385 - 0.800 0.000 1.165 0.800 0.000 0.218 0.443 0.240 1.250 -0.400-0.300CONN Function $\odot \odot$ - 0.160 ø٧ Phase Lock Voltag \odot - 0.000 0.80 RF Out **RF** Signal Out - 0.160 +V Supply Voltage RF OUT 1 ALM Alarm <u>~ 0.300</u> <u>- 0.400</u> GND Ground, Case REF INPUT Reference Signal In Wenzel Associates, Inc. W Austin. Texas Title: Standard 100 MHz-SC Phase Lock Crystal Oscillator P/N· Date: Drawn: Ref: Rev: SPR 501-25058 10-11-11 -Tolerances: 0.XXX Dec: 0.XX Dec: FSCM: (except as noted) Page 1 of 1 62821 ±0.030" ±0.010" Dimensions are in inches