ОИТРИТ
Frequency
2.8 GHz
Level
+13 dBm ±2 dB into 50 ohms
STABILITY
Aging
1 x 10 <sup>-6</sup> first year
after 30 days operating, typical
5 x 10 <sup>-7</sup> second year, typical
3 x 10 <sup>-7</sup> per year thereafter, typical
Phase Noise L(f), typical
100 Hz -99 dBc/Hz
1 KHz -126 dBc/Hz
10 KHz -143 dBc/Hz
100 KHz -144 dBc/Hz
Temperature Stability
±5 x 10 <sup>-7</sup> , 0° to +50°C (Ref +25°C)
Harmonics
≤ -25 dBc
Sub-Harmonics
≤ -60 dBc
Spurious
≤ -80 dBc, excluding power
supply line related spurs
MECHANICAL
Dimensions
3.21 x 4 x 1"
Connectors
SMA(f) and solder pins
Packaging
Nickel-plated machined
aluminum housing – J2
Mounting
Threaded inserts on base,
#2-56, 6 places
POWER REQUIREMENTS
Warm-Up Power
≤ 9.5 Watts for 5 minutes
Total Power
≤ 6.5 Watts at +25°C Supply Voltage
+12 VDC ±5%
· 12 VDO ±0/0

ADJUSTMENT Mechanical Tuning				
±4 x 10 <sup>-6</sup>				
Electrical Tuning				
15 × 10 <sup>-7</sup> 15 VDC				

±5 x 10<sup>-7</sup>, ±5 VDC Negative slope

CRYSTAL

Type

100 MHz SC-cut (x28)

OTHER Label

Use conventional label with the following information: 501-30436 (Current Rev.)

2.8 GHz MXO-FR

+12 VDC

Serial # - Date Code

(Mark connectors with function)

**Test Data** 

Output Level Phase Noise

Temperature Stability Harmonics, Subs, Spurious

Power - Warm-up and Total

Tuning – MT and ET

REV	DATE	REVISION RECORD	DWN	AUTH
-	10-25-16		CB	

J2 MXO Connections		
Connector	Function	
1	Supply Voltage	
2	Ground, Case	
3	Electrical Tuning	
4	RF Output	



