INPUT		
Frequency		
10 MHz		
Level		
+7 dBm ±6 dB into 50 ohms		
OUTPUT		
Frequency		
1.28 GHz		
Level		
+13 dBm $\pm 2$ dB into 50 ohms		
STABILITY		
Aging (free-running)		
1 x 10 <sup>-6</sup> first year		
after 30 days operating, typical		
after 30 days operating, typical 5 x 10 <sup>-7</sup> second year, typical 3 x 10 <sup>-7</sup> per year thereafter, typical		
3 x 10 <sup>-7</sup> per year thereafter, typical		
Phase Noise L(f), typical, (free-running)		
100 Hz -96 dBc/Hz		
1 KHz -126 dBc/Hz		
10 KHz -151 dBc/Hz 100 KHz -152 dBc/Hz		
Temperature Stability		
±5 x 10 <sup>-7</sup> free-running from 0 to +50°C		
(Ref. +25°C)		
Harmonics		
-25 dBc		
Sub-Harmonics		
-60 dBc		
PLL Divider Products		
-60 dBc		
Spurious		
-80 dBc, excluding power		
supply line related spurs		
Phase Lock Alarm		
TTL		
Locked: +3.5 VDC to +5.2 VDC (Hi)		
Out-of-Lock: +0.8 VDC max (Lo)		
Phase Lock Voltage Monitor		
Voltage monitor pin supplied		
MECHANICAL		
Dimensions		

4.4 x 4 x 1"

#### **Connectors**

RF Input/Output: SMA(f)

Power, Monitoring: Feed Thru Terminals

**GND: Ground Turret** 

# **Packaging**

Nickel-plated machined aluminum housing – J2P

#### Mounting

Threaded inserts on base,

#2-56, 6 places

#### POWER REQUIREMENTS

Warm-Up Power

≤ 10 Watts for 5 minutes

#### **Total Power**

≤ 7 Watts at +25°C

# **Supply Voltage**

+12 VDC ±5%

#### **ADJUSTMENT**

### Loop BW

Target Bandwidth: ≤ 10 Hz

Type 2 Loop

#### **CRYSTAL**

#### Type

128 MHz SC-cut (x10)

# **OTHER**

# Label

Use conventional label with the following information:

501-31305 (Current Rev.)

1.28 GHz MXO-PLD

+12 VDC

Serial # - Date Code

(Mark connectors with function)

#### **Test Data**

- Output Level
- Phase Noise free-running
- Temperature Stability free-running
- Harmonics, Subs, Products, Spurious
- Power Warm-up and Total

REV	DATE	REVISION RECORD	DWN	AUTH
-	11-14-17	Initial Release	CB	

J2P MXO Connections			
Connector	Function		
1	Supply Voltage		
2	Ground, Case		
4	RF Output		
5	Phase Lock Voltage		
6	Phase Lock Alarm		
7	External Reference Input		



